

Reconfigurable, Large-Format D-ToF/Photon-Counting SPAD Image Sensors with Embedded FPGA for Scene Adaptability

Tommaso Milanese*, Baris Can Efe*, Claudio Bruschini*,
Nobukazu Teranishi**, Edoardo Charbon*


**AQUA, STI School of Engineering, École polytechnique fédérale de
Lausanne (EPFL), Neuchâtel CH-2000, Switzerland*

***Research Institute of Electronics, Shizuoka University, Hamamatsu, Japan*

Concept & research goals

Consumer LiDAR

Apple iPad Pro LiDAR opening and cross-section



Apple

Auto focus /
presence detection




STMicroelectronics

Biomedical (TOF) PET



Philips – Siemens
– GE Healthcare


X-ray imaging



Park, VLSI24




Security QRNG



Keshavarzian, JSSC,2023


Low-light imaging



Morimoto, IEDM,2021


Scientific

Raman spectroscopy



Maruyama, JSSC,2013


FLIM



Becker & Hickl

SPAD operation


- Photon-to-digital conversion
- SPAD gain $> 10^5$
- Imaging device suited for **digital processing**



▪ Passive quenching and passive recharge


SPAD operation

- Photon-to-digital conversion
- SPAD gain $> 10^5$
- Imaging device suited for **digital processing**



Passive quenching and actively clocked recharge [Charbon 2005]


SPAD imaging platform for rapid prototyping



Illustrations: H. Homulle from Bruschini et al., SPIE, 2023.


SPAD imaging platform for rapid prototyping

Discrete implementation



Milanese, OPEX, 2023


Monolithic implementation



This work

Illustrations: H. Homulle from Bruschini et al., SPIE, 2023.


- Standard FPGA architecture [1]



[1] A. Boutros and V. Betz, "FPGA Architecture: Principles and Progression," in IEEE Circuits and Systems Magazine, vol. 21, no. 2, pp. 4-29.

An FPGA-like architecture

- SPAD + FPGA architecture





SPAD pixel

Research goals: scene adaptability

- An FPGA-based SPAD readout allows real-time scene adaptability

SPAD array camera



High-flux PC



High-flux DToF



Medium-flux DToF




Low-flux DToF

C2 = 2 levels coincidence

C3 = 3 levels coincidence


Scene



Reconfigurable macropixel


Monolithic SPAD readout

- SPAD time multiplexing → high-spatial resolution
- Low-frame rate







Monolithic SPAD readout

- SPAD time multiplexing → high-spatial resolution
- Low-frame rate
- XOR → High-flux photon counting




Monolithic SPAD readout


- SPAD time multiplexing → high-spatial resolution
- Low-frame rate
- XOR → High-flux photon counting
- OR → LiDAR



Spiking neuron-like operation



Spiking neuron-like operation




Spiking neuron-like operation

Spiking neuron-like equation

$$W_s = \boxed{\pi} \cdot \text{SPAD3} + \boxed{\sqrt{2}} \cdot \text{SPAD2} + \boxed{2} \cdot \text{SPAD1} + \boxed{\sqrt{3}} \cdot \text{SPAD0}$$

$$O = \begin{cases} 1 & \text{if } W_s > \boxed{4.94} \\ 0 & \text{otherwise.} \end{cases}$$

$\boxed{}$ = arbitrary numbers



Spiking neuron-like operation

Spiking neuron-like equation


$$W_s = \pi \cdot \text{SPAD3} + \sqrt{2} \cdot \text{SPAD2} + 2 \cdot \text{SPAD1} + \sqrt{3} \cdot \text{SPAD0}$$

$$O = \begin{cases} 1 & \text{if } W_s > 4.94 \\ 0 & \text{otherwise.} \end{cases}$$

□ = arbitrary numbers

LUT table

SPAD3	SPAD2	SPAD1	SPAD0	WS	O
0	0	0	0	0	0
0	0	0	1	1.73	0
0	0	1	0	2	0
0	0	1	1	3.73	0
0	1	0	0	1.41	0
0	1	0	1	3.14	0
0	1	1	0	3.41	0
0	1	1	1	5.15	1
1	0	0	0	3.14	0
1	0	0	1	4.87	0
1	0	1	0	5.14	1
1	0	1	1	6.87	1
1	1	0	0	4.55	0
1	1	0	1	6.29	1
1	1	1	0	6.55	1
1	1	1	1	8.29	1






Results






Monolithic SPAD readout


- Proof-of-concept 110 nm
- 16 SPADs with 5 LUTs
- JTAG: 80 FF x 10 ns = 800 ns programming time





- 1 V excess bias
- 1-2-4-8-16 SPADs



- A photon activates the shutter
- Shutter is stopped by next or later photons





- Coincident photon
- Noise photon



A. Ximenes et al, ISSCC 2019
 P. Padmanabhan, "Direct time-of-flight SPAD image sensors for light detection and ranging.", EPFL thesis, 2021.


- Simulated single-shot TDC
- OR tree piled-up
- 2 levels coincidence performs better



Perspectives




- 3D-stacked technology
- 2x2 SPADs macropixel
- 64x64 SPADs
- 32x32 macropixels proof-of-concept



Architecture for reconfigurable pixels


- Top-level diagram
- JTAG array programming
- Memories for high TAR*
- 3D stacked BSI technology





*TAR = Temporal aperture ratio.

TDC/photon counter


- Window generation circuit
- Generate window only if TDC is programmed for ToF



- Window generation circuit
- Generate window only if TDC is programmed for ToF
- Otherwise GRO [1] doesn't start



[1] Veerappan, Chockalingam, et al. "A 160× 128 single-photon image sensor with on-pixel 55ps 10b time-to-digital converter." *2011 IEEE International Solid-State Circuits Conference*. IEEE, 2011.



- Single macropixel power consumption
 - ToF → 6.9 μ W
 - Intensity → 4.8 μ W
- 1 Mcps per pixel with 2 μ s integration time.
- Estimation on single readout cycle (one exposure + read).

Summary

Summary

- SPAD imaging platform for rapid prototyping
 - Scene adaptability
 - Standard combinations OR - XOR
 - Spiking neuron
- 2D planar proof-of-concept macropixel characterization
 - Linearity
 - Coincidence
- 3D-stacking implementation
 - Low-power sensor modes


Acknowledgements : STMicroelectronics for funding

Thank you


Backup

Intensity vs ToF

- 17b shift register
- SPADs readout with LUT
- 1 flip-flop more for intensity/ToF




- Coincidence detection improves the detection range [1].
- But slows the data capture.







[1] P. Padmanabhan, "Direct time-of-flight SPAD image sensors for light detection and ranging.", EPFL thesis, 2021.

Macropixel 2

- Pixel schematics.
- Provided by STMicro up to the first inverter.
- Reference [1].




[1] Mamdy, B., et al. "A high PDE and high maximum count rate and low power consumption 3D-stacked SPAD device for Lidar applications." *Int. Image Sensor Workshop*. 2023.



- Pulse width.
- PDP.
- DCR.
- Afterpulsing (not observed).



Timing diagram

- Array readout
- High TAR.
- Stream data while integrating.



Jitter - single SPAD

- 3 V excess bias
- Laser <80 ps pw
- TDC LSB 5 ps



- 3 V excess bias
- Laser <80 ps pw
- TDC LSB 5 ps


OR -
M0

N/A -
M1

N/A -
M2

N/A -
M3

M0 select



- 3 V excess bias.
- Laser 40 ps pw.
- TDC LSB 5 ps.


OR -
M0

OR -
M1

OR -
M2


OR -
M3

OR




Dummy correction for timing optimization

- Future implementations
- Avoid timing mismatch
- For timing sensitive applications



SPAD operation

- Photon-to-digital conversion
- SPAD gain $> 10^5$
- Imaging device suited for **digital processing**



Passive quenching and passive recharge

- Maximum countrate – XOR configuration.

